







Drehspul-Messgeräte

für Gleichstrom

Rechteckige Durchbrüche

Klasse 1,5

Querskale (Hochskale im Bestellfall angeben)

Type	 P 48 x 24	 P 72 x 24	 P 96 x 24	 P 144 x 36	
Frontrahmen (mm)	48 x 24	72 x 24	96 x 24	144 x 36	
Durchbruch (mm)	45 x 22	68 x 22	92 x 22	138 x 33	
Skalenlänge (mm)	32	52	60	95	
Gewicht (kg)	0,08	0,10	0,15	0,50	
Messbereichendwert	$R_i / \Delta U$	$R_i / \Delta U$	$R_i / \Delta U$	€	$R_i / \Delta U$ €
μA 100	1000 Ω	680 Ω	3800 Ω	86,10	550 Ω 268,50
150	835 Ω	480 Ω	3800 Ω		420 Ω
250	500 Ω	300 Ω	1300 Ω		250 Ω
400	310 Ω	205 Ω	1100 Ω	81,70	155 Ω 256,90
600	210 Ω	110 Ω	380 Ω		105 Ω
mA 1	33 mV	31 Ω	70 Ω		52 Ω
1,5	46 mV	24 Ω	30 Ω		45 Ω
2,5	46 mV	20 Ω	13 Ω		27 Ω
4	46 mV	17 Ω	5 Ω	78,40	17 Ω 248,50
6	46 mV	60 mV	5 Ω		60 mV
10	46 mV	60 mV	3 Ω		60 mV
15	46 mV	60 mV	2,8 Ω		60 mV
25	46 mV	60 mV	60 mV	81,70	60 mV 256,90
40	46 mV	60 mV	60 mV		60 mV
60	46 mV	60 mV	60 mV		60 mV
100	46 mV	60 mV	60 mV		60 mV
150	46 mV	60 mV	60 mV		60 mV
250	46 mV	60 mV	60 mV	81,70	60 mV 262,50
400	46 mV	60 mV	60 mV		60 mV
600	46 mV	60 mV	60 mV		60 mV
A 1	46 mV	60 mV	60 mV	86,10	60 mV 264,30
an Nebenwiderstand					
mV 60	60 Ω	60 Ω	60 Ω		60 Ω
100	100 Ω	100 Ω	100 Ω	81,40	100 Ω 255,20
150	150 Ω	150 Ω	150 Ω		150 Ω
an Messumformer					
mA 0-20	3 Ω	3 Ω	2,3 Ω	78,00	3 Ω 256,90
4-20	45 Ω	45 Ω	120 Ω	81,70	45 Ω 277,80
V 0-10	10 k Ω	10 k Ω	10 k Ω	81,70	10 k Ω 259,40

ab 1.4.2018
zzgl. 3,8 %
Teuerungszuschlag